

Technical Specifications

Power supply	10 ... 30VDC (Relays work above 19.2V)
Power consumption	typ. 2.4W, max. 4.3W
Power loss at max. load	8.4W
Digital Inputs	Digital inputs: logic 0: 0 ... 2.2V undefined: 2.3 ... 4.9V logic 1: 5 ... 24V Ri=45kΩ useable as frequency counter: frequency: 1 ... 500Hz min. pulse width: 2ms accuracy: +/- 1Hz
Relay Outputs	2 digital relay outputs, dry contact: 250VAC 16A* at cosφ =1 or 30VDC 16A* *Load > 12A: 2.5mm ² / AWG12
Interfaces	Loxone Link, switchable to Tree in software: up to 30 Extensions or 50 Tree devices, max. 500m Loxone Tree: up to 50 Tree devices, max. 500m Loxone Tree Turbo: up to 10 Tree Turbo devices, max. 150m Loxone Air: up to 128 Air devices 868MHz (SRD Band Europe), 4 channels, max. 15.1mW e.r.p. 915MHz (ISM Band Region 2), 10 channels, max. 13.2mW SMA connector Compatible Loxone antennas: SMA Stub Antenna 868 MHz (000200) SMA Rod Antenna 4dBi 868MHz (200151) SMA Antenna 868 MHz (200048) Ethernet: 100Mbps, IPv4/IPv6, HTTPS, SSL/TLS USB 2.0: Type A, max. 500mA

Ambient temperature	0 ... 50°C / 32 ... 122°F
Humidity	max. 95% r.H. (non condensing)
Degree of Protection	IP20

Connecting terminals

	DC Supply, Link, Tree, Tree Turbo	Digital Inputs	Relay Outputs
Terminal type	DG220B	FMC 0,5	MSTB 2,5 HC
Wire cross-section	0.28 ... 0.8mm ² AWG23 ... 18 copper/ aluminium, solid wire only	0,14 ... 0,5mm ² AWG26 ... 20 copper/ aluminium, solid wire only	0.2 ... 2.5mm ² / AWG24 ... 12 Load > 12A: 2.5mm ² / AWG12
Stripping length	5 ... 6mm 0.2 ... 0.24"	7mm / 0,28"	7mm / 0,28"
Tightening torque	-	-	0.5 ... 0.6Nm / 0.37 ... 0.44 lbf ft
Temperature resistance	-40 ... 105°C -40 ... 221°F	-40 ... 70 °C / -40 ... 158°F	-40 ... 70 °C / -40 ... 158°F



For more information
about this product, visit
loxone.com/help/miniserver-compact

Loxone Electronics GmbH
Smart Home 1
4154 Kollerschlag
Austria

Loxone US
3060 Plaza Drive
Suite 105
Garnet Valley,
PA 19060
United States

Loxone UK
The Forum
Station Road
Theale, RG7 4RA
United Kingdom



For additional information,
declaration of conformity, visit
loxone.com/datasheets

Need Help?
loxone.com/support



BACnet is a registered trademark of ASHRAE. ASHRAE does not endorse, approve or test products for compliance with ASHRAE standards. Compliance of listed products to the requirements of ASHRAE Standard 135 is the responsibility of BACnet International. The BTL logo is a registered trademark of BACnet International.

VI600925

LOXONE

Miniserver Compact

Part No.: 100512

About the product

The Miniserver Compact serves as a central control unit for all kinds of automation tasks. Interfaces for Link, Tree, Air and Tree Turbo are integrated for expansion with numerous devices. This way, the Miniserver Compact also serves as an Audioserver.

Installation & electrical connection

The installation of the devices has to be mounted on a DIN rail in an electrical distribution housing (Standard distribution) and may only be performed by qualified personnel.

Protection against electrical contact and fire protection must be provided in the final installation by the use of a standards compliant/approved housing.

To turn the unit on/off during installation and in case of failure, a separator (disconnecting device) must be present. These must be easily accessible and visible.

If the unit is used in a non conform manner as specified by the manufacturer the product included safeguards will be impaired.

Mains and SELV/PELV must not be connected to the relay outputs at the same time.

Information

Contains **FCC ID: 2ARRV-000375**

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation.

CAN ICES-003(B) / NMB-003(B)

